Product Safety Data Sheet

SDS # : 22-00736
2022-02-22
Revision 1

Xerox® VersaLink B7125

Product Description	Multifunction Equipment D-A562 / D-B562
Speed (PPM)	25
Mono / Color	Monochrome

ELECTRICAL INPUT INFORMATION

Voltage (Volts)	**110V-127V**	**220V-240V**
Rated Current (Amperes)	12	8
Frequency (Hertz)	50/60	50/60
Phase Connection	single	single

POWER AND HEAT

	Power (Watts)	**Heat Output (BTU/Hr)**	**Power (Watts)**	**Heat Output (BTU/Hr)**
Active [1]	484	1651.5	488	1665.1
Ready[1]	83	283.2	86	293.4
Sleep[1]	46	157.0	46	157.0
Sleep (2)[1]	1.1	3.75	1.4	4.78
Standby[1] (Off/FEMP) [2]	0.1	0.34	0.4	1.36

[1] Power states defined per ENERGY STAR Program requirements for Imaging Equipment
[2] FEMP - Federal Energy Management Program
Note: The electrical power information provided should not be used to define the electrical support required for this product. Consult your Xerox representative if you require detailed information.

OPERATING ENVIRONMENT

Relative Humidity %	10-85%		
Ambient Temperature	50-90 °F	/	10-32 °C

PRODUCT SIZE

Depth	26.4 in.	67.8 cm
Width	23.2 in.	59.0 cm
Height	30.2 in.	76.8 cm
Weight	113.1 lbs	51.3 kg

SPACE REQUIREMENTS

Refer to Users Guide
For additional information regarding different configurations please contact your local sales representative.

LIGHT SOURCE

LED

CHEMICAL EMISSIONS

Chemical Emission Test Method RAL-UZ171
The machine was tested under the conditions as specified in the standard inside a room of 2.0 m^3 with 4.0 air changes per hour.

PARAMETER	**Emission Rate**
TVOC	2.2 mg/h
Dust	None detected
Ozone	None detected
Styrene	None detected
Benzene	None detected

Product Safety Data Sheet

ACOUSTICAL NOISE

	Sound Power Level LwAd (B)	Sound Pressure Level LpAd (dBA)
Standby	3.3	15.9
Run	6.6	57.7

Xerox Corporation has developed this Product Safety Data sheet for informational purposes as a courtesy for Xerox customers. Any determination regarding the proper use of this information must be made by the user, including any use of the information for compliance with applicable laws, rules and regulations. Xerox believes the information herein to be accurate as of the date of issuance but makes no representations or warranties of any kind, either express or implied, as to the accuracy, completeness or fitness for use of the information. By issaunce of this Product Safety Data Sheet, Xerox does not assume any liability or responsibility for losses, claims, liabilities or damages which may result from reliance upon the information herein.

Inquiries U.S. Only: 1-800-275-9376
Contact U.S. Only: askxerox@xerox.com
Contact Non-U.S. Only: ehs-europe@xerox.com